

Corridor Light



To Install near the ward and door to notify the ward when patient calls doctor or nurse.

Features & Functions

- Corridor light has a dome cover on the plate.
- Dome Cover : Material made to plastic white color
- Plate : Plate made to plastic white color
- Voltage range : 12 and 24 VDC
- LED circuit : 6 RGB LED, 2 Color in 1 LED, Which show the red color or green color.
- Operating current : RGB LED

Red Color	50 mA at 12 VDC / LED Circuit
	50 mA at 24 VDC / LED Circuit
Green Color	30 mA at 12 VDC / LED Circuit
	40 mA at 24 VDC / LED Circuit
- Easy to attach and detach as well as to install.
- Design modern and stable shape.
- Lamp indicates general call, presence call, emergency call and medical team call.

CL-302I(N)

